

Version : <u>1.1</u>

## TECHNICAL SPECIFICATION

## MODEL NO.: PD104SL5

Customer's Confirmation

Customer Name

Date

Ву

PVI's Confirmation

Confirmed By

Date:Mar,10, 2003

This technical specification is subject to change without notice. Please contact with PVI for more detail information about this specification sheet.



# TECHNICAL SPECIFICATION

# <u>CONTENTS</u>

<i>NO</i> .	ITEM	PAGE
-	Cover	1
-	Contents	2
1	Application	3
2	Features	3
3	Mechanical Specifications	3
4	Mechanical Drawing of TFT-LCD module	4
5	Input / Output Terminals	6
6	Absolute Maximum Ratings	8
7	Electrical Characteristics	8
8	Power On Sequence	14
9	Optical Characteristics	15
10	Handling Cautions	18
11	Reliability Test	19
12	Block Diagram	20
13	Packing	21
-	Revision History	24

The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:2

#### 1.Application

This data sheet applies to a color TFT LCD module, PD104SL5.

PD104SL5 module applies to OA product, car TV(must use Analog to Digital drive board), which require high quality flat panel display. If you must use in high reliability environment can't over reliability test condition

Prime View assume no responsibility for any damage resulting from the use of the device which dose not comply with the instructions and the precautions in these specification sheet.

#### 2. Features

- . Amorphous silicon TFT LCD panel with back-light unit
- . Pixel in stripe configuration

PRIME VIEW

- . Slim and compact, designed for O/A application
- . Display Colors : 262,144 colors
- . Optimum Viewing Direction : 12 o'clock
- . 3.3V LVDS interface standard: DS90CF364 as receiver
- . +3.3V DC supply voltage for TFT LCD panel driving
- . Backlight driving DC/AC inverter not included in this module
- . Wide Viewing Angle

#### **3.Mechanical Specifications**

Parameter	Specifications	Unit
Screen Size	26.4(diagonal)	cm
	10.4 (diagonal)	inch
Display Format	800×(R, G, B)×600	dot
Display Colors	262,144	
Active Area	211.2(H)×158.4 (V)	mm
Pixel Pitch	0.264 (H)×0.264 (V)	mm
Pixel Configuration	Stripe	
Outline Dimension	243 (w)×185.1(H)×11(typ.) (D)	mm
Weight	480(typ.),	g
Back-light	CCFL, 2 tubes	
Surface treatment	Anti-glare and hard-coating	
Display mode	Normally white	

The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:3

#### 4. Mechanical Drawing of TFT-LCD Module



The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:4

PRIME VIEW



The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:5

#### 5.Input Terminals

5-1) TFT-LCD Panel Driving

Connector type: Molex 55177-1491

Pin No.	Symbol	Function	Remark
1	VDD	Power supply : +3.3V	
2	VDD	Power supply : +3.3V	
3	GND		
4	GND		
5	IN0-	Pixel data Transmission pair 0 (negative -)	
6	IN0+	Pixel data Transmission pair 0 (positive +)	
7	IN1-	Pixel data Transmission pair 1 (negative -)	
8	IN1+	Pixel data Transmission pair 1 (positive +)	
9	IN2-	Pixel data Transmission pair 2 (negative -)	
10	IN2+	Pixel data Transmission pair 2 (positive +)	
11	CLK-	Sampling Clock (negative -)	
12	CLK+	Sampling Clock (positive +)	
13	GND		
14	GND		

Recommended Transmitter (DS90C\*363 of National Semiconductor) to PD104SL5 interface Assignment:

Assignm					
	Terminal 90C*363		Graphic controller output signal	Output signal symbol	To PD104SL5 interface terminal(Symbol)
Symbol	No.	Symbol	Function		
TIN0	44	R0	Red pixel data (LSB)	<u>ר</u>	
TIN1	45	R1	Red pixel data		
TIN2	47	R2	Red pixel data	Tout0	— No.5 : IN0-
TIN3	48	R3	Red pixel data	>	
TIN4	1	R4	Red pixel data	Tout0+	—No.6 : IN0+
TIN5	3	R5	Red pixel data(MSB)		
TIN6	4	G0	Green pixel data (LSB)	/	
TIN7	6	G1	Green pixel data	>	
TIN8	7	G2	Green pixel data		
TIN9	9	G3	Green pixel data	Tout1- —	—No.7 : IN1-
TIN10	10	G4	Green pixel data	>	
TIN11	12	G5	Green pixel data(MSB)	Tout1+	—No.8 : IN1+
TIN12	13	B0	Blue pixel data(LSB)		
TIN13	15	B1	Blue pixel data	)	
TIN14	16	B2	Blue pixel data	7	
TIN15	18	B3	Blue pixel data		
TIN16	19	B4	Blue pixel data	Tout2- —	— No.9 : IN2-
TIN17	20	B5	Blue pixel data(MSB)		
TIN18	22	NC	No connection	Tout2+	—N0.10 : IN2+
TIN19	23	NC	No connection		
TIN20	25	ENAB	Compound Synchronization signal	7	
CLK in	26	NCLK	Data sampling clock	TCLK out-	No.11 : CLK IN-
				TCLK out+	No.12 : CLK IN+

The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:6



#### LVDS Interface Block Diagram



#### 5-2) Backlight driving

Connector type : "BHR-02VS-1" of Japan Solderless Terminal MFG Co. LTD

	PIN NO.	Symbol	Description	Remark				
	1	LV	Ground	White				
I	2	HV	Lamp power input	Pink (or Gray)				
	3	HV	Lamp power input	Pink (or Gray)				

The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:7

#### 6.Absolute Maximum Ratings:

				GND=0	<b>/</b> , Ta=25℃
Parameters	Symbol	MIN.	MAX.	Unit	Remark
Supply Voltage	V <sub>DD</sub>	-0.3	+4.0	V	
Input Signals Voltage	V <sub>IN</sub>	-0.3	VDD+0.3	V	Note 6-1
Backlight Driving Voltage	VL	-	2000	V	
Backlight Driving Frequency	FL	0	100	KHz	
Storage Temperature	T <sub>ST</sub>	-20	+60	°C	Note 6-2
Operating Temperature	T <sub>OP</sub>	0	+50	°C	

Note 6-1: LVDS signal

Note 6-2: Humidity : 80% RH Max. at Ta  $\leq$  40°C.

Maximum wet-bulb temperature is at 39°C or less at Ta > 40°C and no condensation.

#### 7. Electrical Characteristics

7-1) Recommended Operating Conditions: $GND = 0V$ , Ta = $25^{\circ}C$										
Item	Symbol	Min.	Тур.	Max.	Unit	Remark				
Supply Voltage	VDD	3.0	3.3	3.6	V					
Current Dissipation	I <sub>DD</sub>	-	350	450	mA	Note 7-1				
LVDS Differential input high threshold	Vth	-	-	100	mV	Note 7-2				
LVDS Differential input low threshold	Vtl	-100	-	-						
Lamp Current	I <sub>FL</sub>	6.0	14.0	16.0	mA	Note 7-3				
						Note 7-5				
Lamp Voltage	VL	400	550	600	Vrms	Note 7-3				
Lamp Initial Voltage	$V_{SFL}$	-	-	875	Vrms	at Ta=25°C				
						Note 7-4				
		-	-	1300		at Ta=0°C				
						Note 7-4				
Lamp Driving Frequency	FL	30	55	60	KHz					
Lamp power consumption		4	8	11	W	Note 7-5				
Lamp Life Time		10000	15000		Hrs	Note 7-6				
LCD Panel Life Time(MTBF)			50000		Hrs					

Note 7-1 : To test the current dissipation of VDD, using the "color bars" testing pattern shown as below

1 2 3 4 5 6 7 8	
-----------------	--

Idd current dissipation testing pattern

- 4. Green
- 5. Magenta
- 6. Red
- 7. Blue
- 8. Black

<sup>1.</sup> White

<sup>2.</sup> Yellow

<sup>3.</sup> Cyan

PRIME VIEW

Note 7-2 : Please refers to DS90CF364 specification by National Semiconductor Corporation. This LCD module conforms to LVDS standard.

- Note 7-3 : The back-light driving waveform should be as closed to sine-wave as possible. In order to satisfy the quality of B/L, no matter use what kind of inverter, the output lamp current must between Min. and Max. to avoid the abnormal display image caused by B/L.
- Note 7-4 : Not including the efficiency of backlight DC/AC inverter
- Note 7-5 : Lamp current is measured with current meter for high frequency as shown below



Lamp current dissipation testing configuration

Note 7-6: The life time is determined as the time at which brightness of lamp is 50% compare to that of initial value at the typical lamp current.

7-2) Input / Output signal timing chart(A) Vertical Timing



The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:9

**O**PRIME VIEW

PD104SL5



The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:10

#### D) Timing Specifications

Item	symbol	Min.	Тур.	Max.	Unit	Remark
Frame Cycling	t1	604 X t3	628 X t3	800 X t3		
			16.58		ms	
Vertical Display Period	t2	600 X t3	600 X t3	600 X t3		
Horizontal Scanning Time	t3	920X t5	1056 X t5	1064 X t5		
			26.4		us	
Horizontal Display Period	t4	800 X t5	800 X t5	800 X t5		
Clock Cycle	t5		25.0		ns	
Clock High Level Time	t6	9.0			ns	
Clock Low Level Time	t7	9.0			ns	
Hold time	t8	4.0			ns	
Setup time	t9	5.0			ns	

#### 7-3) Display Color and Gray Scale Reference

PRIME VIEW

								In	put	t Co	olor	Da	ta						
Co	Red Green								Blue										
		R5	<b>R4</b>	R3	R2	<b>R1</b>	R0	G5	G4	G3	G2	G1	G0	B5	<b>B4</b>	<b>B</b> 3	B2	<b>B1</b>	<b>B0</b>
	Black	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red (63)	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0
	Green (63)	0	0	0	0	0	0	1	1	1	1	1	1	0	0	0	0	0	0
Basic	Blue (63)	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1
Colors	Cyan	0	0	0	0	0	0	1	1	1	1	1	1	1	1	1	1	1	1
	Magenta	1	1	1	1	1	1	0	0	0	0	0	0	1	1	1	1	1	1
	Yellow	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0	0	0
	White	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
	Red (00)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red (01)	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0
	Red (02)	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0
	Darker																		
Red	$\downarrow$	↓	$\downarrow$	$\downarrow$	V	$\downarrow$	$\downarrow$	$\downarrow$	$\downarrow$	$\downarrow$	$\downarrow$	$\downarrow$	$\downarrow$	↓	$\downarrow$	$\downarrow$	↓	$\downarrow$	↓
	Brighter																		
	Red (61)	1	1	1	1	0	1	0	0	0	0	0	0	0	0	0	0	0	0
	Red (62)	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red (63)	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0
	Green (00)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Green (01)	0	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0
	Green (02)	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0
	Darker																		
Green	$\downarrow$	↓	$\downarrow$	¥	Ŷ	$\downarrow$	↓	$\downarrow$	$\rightarrow$	$\downarrow$	$\rightarrow$	$\downarrow$	↓						
	Brighter																		
	Green (61)	0	0	0	0	0	0	1	1	1	1	0	1	0	0	0	0	0	0
	Green (62)	0	0	0	0	0	0	1	1	1	1	1	0	0	0	0	0	0	0
	Green (63)	0	0	0	0	0	0	1	1	1	1	1	1	0	0	0	0	0	0
	Blue (00)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Blue (01)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1
	Blue (02)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0
	Darker																		
Blue	$\downarrow$	$\downarrow$	$\downarrow$	$\downarrow$	$\downarrow$	$\downarrow$	$\downarrow$	$\downarrow$	↓	$\downarrow$	$\downarrow$								
	Brighter																		
	Blue (61)	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	0	1
	Blue (62)	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	0
	Blue (63)	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1



#### 7-4) Pixel Arrangement

The LCD module pixel arrangement is the stripe.

	GB GB Pixel
$1 \text{ Pixel} = \mathbb{R} \mathbb{G} \mathbb{B}$	
R G B R G B 599 th Line	KGB KGB



# 8. Power On Sequence

- 1. The supply voltage for input signals should be same as  $V_{CC.}$
- 2. When the power is off , please keep whole signals (Hsync, Vsync, CLK, Data) low level or high impedance

The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:14

OF°C

#### 9.) Optical Characteristics

#### 9-1) Specification:

Ta = 25°C													
Parame	eter	Symbol	Condition	MIN.	TYP.	MAX.	Unit	Remarks					
	Horizontal	θ		±55	±60	-	deg						
Viewing Angle	Vertical	$\theta$ (to 12 o'clock)	CR≥10	50	55	-	deg	Note 9-1					
	ventical	$\theta$ (to 6 o'clock)		35	40	-	deg						
Contrast Ratio		CR	Optimum direction	100	180	-	-	Note 9-2					
Boononco timo	Rise	Tr	<i>θ</i> =0°	-	15	50	ms	Note 9-4					
Response time	Fall	Tf	$\varphi = 0^{\circ}$	-	25	50	ms	NOLE 9-4					
Luminance	-	L	$\theta = 0^{\circ} / \varphi = 0^{\circ}$	300	350	-	<b>cd/</b> m <sup>2</sup>	Note 9-3					
Luminance Unifo	ormity	U		55	80	-	%	Note 9-5					
White Chromaticity		х		0.280	0.310	0.340	-						
		у		0.310	0.340	0.370	-						
		TC		5300	5700	6100	K						
Cross Talk Ratio	)	CTK		-	-	3.5	%	Note 9-6					

All the optical measurement shall be executed 30 minutes after backlight being turn-on. The optical characteristics shall be measured in dark room (ambient illumination on panel surface less than 1 Lux). The measuring configuration shows as following figure.



Optical characteristics measuring configuration

The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:15

# **O**PRIME VIEW

Note 9-1`: The definitions of viewing angles are as follows.



Note 9-2 : The definition of contrast ratio	$CP = \frac{\text{Luminance at gray level 63}}{\text{Luminance at gray level 63}}$
	CR = Luminance at gray level 0

Note 9-3 : Topcon BM-5A luminance meter 2°field of view is used in the testing (after 30 minutes' operation). The typical luminance value is measured at lamp current 14.0 mA.

Note 9-4: Definition of Response Time Tr and Tr:





U = The Minimum Brightness of the 9 testing Points The Maximum Brightness of the 9 testing Points Luminance meter : BM-5A or BM-7 fast(TOPCON) Measurement distance : 500 mm +/- 50 mm Ambient illumination : < 1 Lux Measuring direction : Perpendicular to the surface of module

The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:16



The test pattern is white (Gray Level 63).



Note 9-6: Cross Talk (CTK) = YA-YB YA: Brightness of Pattern A YB: Brightness of Pattern B Luminance meter : BM 5A (TOPCON) Measurement distance : 500 mm +/- 50 mm Ambient illumination : < 1 Lux Measuring direction : Perpendicular to the surface of module



The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:17

#### 10. Handling Cautions

- 10-1) Mounting of module
  - a) Please power off the module when you connect the input/output connector.
  - b) Please connect the ground pattern of the inverter circuit surely. If the connection is not perfect, some following problems may happen possibly.
    - 1. The noise from the backlight unit will increase.
    - 2. The output from inverter circuit will be unstable.
    - 3.In some cases a part of module will heat.
  - c) Polarizer which is made of soft material and susceptible to flaw must be handled carefully.
  - d) Protective film (Laminator) is applied on surface to protect it against scratches and dirts. It is recommended to peel off the laminator before use and taking care of static electricity.
- 10-2) Precautions in mounting
  - a) When metal part of the TFT-LCD module (shielding lid and rear case) is soiled, wipe it with soft dry cloth.
  - b) Wipe off water drops or finger grease immediately. Long contact with water may cause discoloration or spots.
  - c) TFT-LCD module uses glass which breaks or cracks easily if dropped or bumped on hard surface. Please handle with care.
  - d) Since CMOS LSI is used in the module. So take care of static electricity and earth yourself when handling.
- 10-3) Adjusting module
  - a) Adjusting volumes on the rear face of the module have been set optimally before shipment.
  - b) Therefore, do not change any adjusted values. If adjusted values are changed, the specifications described may not be satisfied.
- 10-4) Others
  - a) Do not expose the module to direct sunlight or intensive ultraviolet rays for many hours.
  - b) Store the module at a room temperature place.
  - c) The voltage of beginning electric discharge may over the normal voltage because of leakage current from approach conductor by to draw lump read lead line around.
  - d) If LCD panel breaks, it is possibly that the liquid crystal escapes from the panel. Avoid putting it into eyes or mouth. When liquid crystal sticks on hands, clothes or feet. Wash it out immediately with soap.
  - e) Observe all other precautionary requirements in handling general electronic components.
  - f) Please adjust the voltage of common electrode as material of attachment by 1 module.

The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:18

#### 11. Reliability Test

No	Test Item	Test Condition	Remark	
1	High Temperature Storage Test	Ta = +60℃, 240 hrs		
2	Low Temperature Storage Test Ta = $-20^{\circ}$ C, 240 hrs			
3	Low Temperature Operation Test	Temperature Operation Test Ta = $0^{\circ}$ C, 240 hrs		
4	High Temperature & High Humidity	Ta = +50 $^\circ\!\mathrm{C}$ , 80%RH, 240 hrs		
4	Operation Test	(No Condensation)		
_	Thermal Cycling Test	0°C		
5	(non-operating)	1Hr 0.5Hr 1Hr		
6		Frequency : 10 ~ 57 $H_Z$ , Amplitude : 0.15 mm 58~500Hz, 1G		
	Vibration Test	Sweep time: 11 min		
	(non-operating)	Test Period: 3 hrs (1 hr for each direction of X,		
		Y, Z)		
-	Shock Test	80G, 6ms, X,Y, Z		
7	(non-operating)	1 times for each direction		
		C=150pF,R=330Ω		
8	Electron Static Discharge	Contact=±8KV		
ð	Election Static Elsenarge	Air=±15KV		
		10 times/terminal		

Ta: ambient temperature

#### [Judgement Criteria]

Under the display quality test conditions with normal operation state , there should be no change which may affect practical display function.

The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:19

#### 12.)Block Diagram



The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:20

# **O**PRIME VIEW

#### 13.)Packing











The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:23

### **Revision History**

Rev.	Issued Date	Revised Content
1.0	Mar.27, 2002	New
1.1	10 0000	Modify : 1.page 03 : Mechanical Specifications Weight from 470g to 480g . 2.page 05 : Rear View . 3.page 08 : Lamp Life Time to 15000 hrs . 4.page 10 : D)Timing specifications . Frame cycling from 660×t3 to
		800xt3, Horizontal Scanning Time from 844xt5 to 920xt5. 5.page 15: White Chromaticity ( x from 0.33 to 0.31, y 0.39 to 0.34).

The information contained herein is the exclusive property of Prime View International Co., Ltd. and shall not be distributed, reproduced, or disclosed in whole or in part without prior written permission of Prime View International Co., Ltd. Page:24